LCD / LCM SPECIFICATION



WINSTAR Display Co.,Ltd. 華凌光電股份有限公司



SPECIFICATION

CUSTOMER :

MODULE NO.:

WH1601L-TMI-CT#

APPROVED BY:		
(FOR CUSTOMER USE ONLY)	PCB VERSION:	DATA:

SALES BY	APPROVED BY	CHECKED BY	PREPARED BY

VERSION	DATE	REVISED PAGE NO.	SUMMARY
E	2019/08/27		Modify Material List of Components for RoHs

	Winstar Display Co., LTD MODLE NO: 華凌光電股份有限公司											
REC	ORDS OF REV	VISION	DOC. FIRST ISSUE									
VERSION	DATE	REVISED PAGE NO.	SUMMARY									
0	2007/12/20		First issue									
А	2011/11/21		Correct ST7066IC									
			information.									
В	2014/11/27		Remove IC information									
			Modify B/L information									
С	2016/01/27		Modify Precautions in use									
			of LCD Modules									
			& Static electricity test									
D	2017/01/19		Modify Backlight									
			Information									
E	2019/08/27		Modify Material List of									
			Components for RoHs									

Contents

- 1. Module Classification Information
- 2.Precautions in use of LCD Modules
- **3.General Specification**
- 4. Absolute Maximum Ratings
- **5.**Electrical Characteristics
- **6.Optical Characteristics**
- 7.Interface Pin Function
- 8.Contour Drawing &Block Diagram
- 9. Character Generator ROM Pattern
- 10.Reliability
- 11.Backlight Information
- 12.Inspection specification
- 13. Material List of Components for RoHs
- 14.Recommendable Storage

1.Module Classification Information W 1601 T <u>CT#</u> Η L Μ Ī (1) (2) 4 (5) 6) \bigcirc 3 (8)

① Brand: WINSTAR DISPLAY CORPORATION

② Display Type : H→Character Type, G→Graphic Type, T→TAB Type

③ Display Font : Character 16 words, 01 Lines.

④ Model serials no.

5	Backlight	$N \rightarrow Without backlight$	T→LED	, White	L→LED, Full color
	Type:	$B \rightarrow EL$, Blue green	A→LED	, Amber	J→DIP LED,Blue
		$D \rightarrow EL$, Green	R→LED	, Red	$K \rightarrow DIP LED, White$
		$W \rightarrow EL$, White	O→LED	, Orange	$E \rightarrow DIP LED$, Yellow Green
		M→EL, Yellow Green	G→LED	, Green	H→DIP LED,Amber
		$F \rightarrow CCFL$, White	$P \rightarrow LED$, Blue	$I \rightarrow DIP LED, Red$
		$Y \rightarrow LED$, Yellow Green	X→LED	, Dual color	
		$G \rightarrow LED$, Green	C→LED	, Full color	
6	LCD Mode :	B→TN Positive, Gray		V→FSTN	Negative, Blue
		N→TN Negative,		T→FSTN	Negative, Black
		$L \rightarrow VA$ Negative		D→FSTN	Negative (Double film)
		$H \rightarrow HTN$ Positive, Gray	7	F→FSTN	Positive
		I→HTN Negative, Black		$K \rightarrow FSC N$	legative
		U→HTN Negative, Blue		$S \rightarrow FSC Po$	ositive
		$M \rightarrow STN$ Negative, Blue		E→ISTN N	Negative, Black
		G→STN Positive, Gray		C→CSTN	Negative, Black
		Y→STN Positive, Yellow	v Green	A→ASTN	Negative, Black
\bigcirc	LCD Polarizer	$A \rightarrow Reflective, N.T, 6:00$)	H→Transfle	ctive, W.T,6:00
	Type/	$D \rightarrow Reflective, N.T, 12:0$	0	K→Transfle	ctive, W.T,12:00
	Temperature	$G \rightarrow Reflective, W. T, 6:0$	0	C→Transmis	ssive, N.T,6:00
	range/ View	$J \rightarrow Reflective, W. T, 12:0$	00	F→Transmis	ssive, N.T,12:00
	direction	$B \rightarrow$ Transflective, N.T,6:	00	I→Transmis	sive, W. T, 6:00
		$E \rightarrow$ Transflective, N.T.12	:00	L→Transmis	ssive, W.T,12:00
8	Special Code	CT:English and Cyrillic s	standard fo	ont	
		#:Fit in with the ROHS I	Directions	and regulation	ns

2.Precautions in use of LCD Modules

- (1)Avoid applying excessive shocks to the module or making any alterations or modifications to it.
- (2)Don't make extra holes on the printed circuit board, modify its shape or change the components of LCD module.
- (3)Don't disassemble the LCM.
- (4)Don't operate it above the absolute maximum rating.
- (5)Don't drop, bend or twist LCM.
- (6)Soldering: only to the I/O terminals.
- (7)Storage: please storage in anti-static electricity container and clean environment.
- (8) Winstar have the right to change the passive components, including R3,R6 & backlight adjust resistors. (Resistors, capacitors and other passive components will have different appearance and color caused by the different supplier.)
- (9)Winstar have the right to change the PCB Rev. (In order to satisfy the supplying stability, management optimization and the best product performance...etc, under the premise of not affecting the electrical characteristics and external dimensions, Winstar have the right to modify the version.)
- (10) To ensure the stability of the display screen, please apply screen saver after showing 30 mins of fixed display content.

3.General Specification

Item	Dimension	Unit
Number of Characters	16 characters x 1Lines	—
Module dimension	122.0 x 33.0 x 13.5 (MAX)	mm
View area	99.0 x 13.0	mm
Active area	94.84 x 9.66	mm
Dot size	0.92 x 1.1	mm
Dot pitch	0.98 x 1.16	mm
Character size	4.84 x 8.06	mm
Character pitch	6.0 x 8.56	mm
LCD type	STN Negative, Blue Transmissive (In LCD production, It will occur slightly color of can only guarantee the same color in the same ba	
Duty	1/16	
View direction	6 o'clock	
Backlight Type	LED ,White	
IC	ST7066U	

4.Absolute Maximum Ratings

Item	Symbol	Min	Тур	Max	Unit
Operating Temperature	Т _{ОР}	-20	_	+70	°C
Storage Temperature	T _{ST}	-30		+80	°C
Input Voltage	VI	V _{SS}	_	V _{DD}	V
Supply Voltage For Logic	VDD-V _{SS}	-0.3		7	V
Supply Voltage For LCD	V _{DD} -V _o	-0.3		13	V

5.Electrical Characteristics

Item	Symbol	Condition	Min	Тур	Max	Unit
Supply Voltage For Logic	V_{DD} - V_{SS}		4.5	5.0	5.5	V
Supply Voltage For LCD		Ta=-20°C	_		5.5	V
*Note	V_{DD} - V_0	Ta=25°C	4.2	4.35	4.5	V
		Ta=70°C	3.5	_	_	V
Input High Volt.	V _{IH}	_	$0.7 V_{DD}$		V _{DD}	V
Input Low Volt.	V _{IL}	_	Vss		0.6	V
Output High Volt.	V _{OH}		3.9		VDD	V
Output Low Volt.	V _{OL}		0		0.4	V
Supply Current	I _{DD}	V _{DD} =5.0V	1.0	1.2	1.5	mA

* Note: Please design the VOP adjustment circuit on customer's main board



6.Optical Characteristics

Item	Symbol	Condition	Min	Тур	Max	Unit
	θ	$CR \ge 2$	0	—	20	$\Psi = 180^{\circ}$
X7: A1-	θ	$CR \ge 2$	0		40	$\Psi = 0^{\circ}$
View Angle	θ	$CR \ge 2$	0		30	$\Psi = 90^{\circ}$
	θ	$CR \ge 2$	0		30	$\Psi = 270^{\circ}$
Contrast Ratio	CR	_		3		
D	T rise	_	—	150	200	ms
Response Time	T fall	_	—	150	200	ms

Definition of Operation Voltage (Vop)





Definition of Response Time (Tr, Tf)





Conditions :

Operating Voltage : Vop Frame Frequency : 64 HZ Definition of viewing $angle(CR \ge 2)$ Viewing Angle(θ , ϕ) : 0° , 0° Driving Waveform : 1/N duty , 1/a bias



7.Interface Pin Function

Pin No.	Symbol	Level	Description
1	V _{SS}	0V	Ground
2	V_{DD}	5.0V	Supply Voltage for logic
3	VO	(Variable)	Operating voltage for LCD
4	RS	H/L	H: DATA, L: Instruction code
5	R/W	H/L	H: Read L: Write
6	Е	H,H→L	Chip enable signal
7	DB0	H/L	Data bit 0
8	DB1	H/L	Data bit 1
9	DB2	H/L	Data bit 2
10	DB3	H/L	Data bit 3
11	DB4	H/L	Data bit 4
12	DB5	H/L	Data bit 5
13	DB6	H/L	Data bit 6
14	DB7	H/L	Data bit 7
15	А	_	Power supply for B/L(+)
16	K	_	Power supply for B/L(-)

8.Contour Drawing & Block Diagram



8.56 8.06 1.16 DOT SIZE

The non-specified tolerance of dimension is ± 0.3 mm.

S = 3 : 1



Character located	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	
DDRAM address	00	01	02	03	04	05	06	07	40	41	42	43	44	45	46	47	

2-line display mode.

9.Character Generator ROM Pattern

Table.2

67-64 63-60	0000	0001	0010	0011	0100	0101	0110	0111	1000	1001	1010	1011	1100	1101	1110	1111
0000	CG RAM (1)															
0001	(2)															
0010	(3)															
0011	(4)															
0100	(5)															
0101	(6)															
0110	0															
0111	(8)															
1000	(1)															
1001	(2)															
1010	3															
1011	(4)															
1100	(5)															
1101	(6)															
1110	0															
1111	(8)															

WINSTAR

10.Reliability

Content of Reliability Test (Wide temperature, -20°C~70°C)

Environmental Test							
Test Item	Content of Test	Test Condition	Not e				
High Temperature storage	Endurance test applying the high storage temperature for a long time.	80°C 200hrs	2				
Low Temperature storage	Endurance test applying the low storage temperature for a long time.	-30°C 200hrs	1,2				
High Temperature Operation	Endurance test applying the electric stress (Voltage & Current) and the thermal stress to the element for a long time.	70℃ 200hrs					
Low Temperature Operation	Endurance test applying the electric stress under low temperature for a long time.	-20°C 200hrs	1				
High Temperature/ Humidity storage	The module should be allowed to stand at 60 °C,90%RH max For 96hrs under no-load condition excluding the polarizer, Then taking it out and drying it at normal temperature.	60°C ,90%RH 96hrs	1,2				
Thermal shock resistance	The sample should be allowed stand the following 10 cycles of operation $-20^{\circ}C$ $25^{\circ}C$ $70^{\circ}C$ 30min 5min 30min 1 cycle	-20°C/70°C 10 cycles					
Vibration test	Endurance test applying the vibration during transportation and using.	Total fixed amplitude : 1.5mm Vibration Frequency : 10~55Hz One cycle 60 seconds to 3 directions of X,Y,Z for Each 15 minutes	3				
Static electricity test	Endurance test applying the electric stress to the terminal.	$VS=\pm 600V(contact),$ $\pm 800v(air),$ $RS=330\Omega$ CS=150pF 10 times					

Note1: No dew condensation to be observed.

Note2: The function test shall be conducted after 4 hours storage at the normal

Temperature and humidity after remove from the test chamber.

Note3: The packing have to including into the vibration testing.

11.Backlight Information

Specification

PARAMETER	SYMBOL	MIN	ТҮР	MAX	UNIT	TEST CONDITION
Supply Current	ILED	10	32	40	mA	V=3.5V(Note 1)
Supply Voltage	V	3.4	3.5	3.6	V	-
Reverse Voltage	VR	_	_	5	V	-
Luminance (Without LCD)	IV	480	600	_	CD/M ²	ILED=32mA
LED Life Time (For Reference only)	_	_	50K	_	Hr.	ILED=32mA 25°C ,50-60%RH, (Note 2)
Color	White		1			

Note: The LED of B/L is drive by current only, drive voltage is for reference only. drive voltage can make driving current under safety area (current between minimum and maximum).

Note 1: Supply current minimum value is only for reference since LED brightness efficiency keeps enhancing. Current consumption becomes less and less to achieve the same luminance.

Note 2:50K hours is only an estimate for reference.

2.Drive from pin15,pin16



ill never get Vee output from pin15)

12.Inspection specification

NO	Item	Criterion				AQL
01	Electrical Testing Black or	Missing charact Display malfun No function or Current consum LCD viewing a Mixed product Contrast defect.	ter , dot or ction. no display. nption exce ngle defec types.	eeds product specif t.	ications.	0.65
02	white spots on LCD (display only)	 2.1 White and black spots on display ≤0.25mm, no more than three white or black spots present. 2.2 Densely spaced: No more than two spots or lines within 3mm 				2.5
03	LCD black spots, white spots, contamination (non-display)	3.1 Round type $\Phi = (x + y) / 2$ \longrightarrow 3.2 Line type : 0 \downarrow \downarrow \downarrow \downarrow \downarrow \downarrow \downarrow \downarrow	↓ Ŧ ^Y	SIZE $\Phi \le 0.10$ $0.10 < \Phi \le 0.20$ $0.20 < \Phi \le 0.25$ $0.25 < \Phi$	Acceptable Q TY Accept no dense 2 1 0 Acceptable Q TY Accept no dense 2 Accept no dense 2 As round type	2.5
04	Polarizer bubbles	If bubbles are v judge using bla specifications, 1 to find, must ch specify directio	ck spot not easy neck in	Size Φ $\Phi \le 0.20$ $0.20 < \Phi \le 0.50$ $0.50 < \Phi \le 1.00$ $1.00 < \Phi$ Total Q TY	Acceptable Q TY Accept no dense 3 2 0 3	2.5

Scratches	Symbols Define: x: Chip length k: Seal width L: Electrode pad leng 6.1 General glass chip		Chip thickness LCD side length	
	 x: Chip length k: Seal width L: Electrode pad leng 6.1 General glass chip 	t: Glass thickness a: I gth: p :	CD side length	
		MY No 100		
Chipped	z: Chip thickness $Z \leq 1/2t$	y: Chip width Not over viewing area	x : Chip length $x \le 1/8a$	2.5
g1055	$1/2t < z \leq 2t$	Not exceed 1/3k	$x \leq 1/8a$	
	⊙ If there are 2 or mo 6.1.2 Corner crack:	bre chips, x is total lengt	h of each chip.	
	z: Chip thickness	y: Chip width	x: Chip length]
	$Z \leq 1/2t$	Not over viewing area	x≤1/8a	
	$1/2t < z \leq 2t$	Not exceed 1/3k	$x \leq 1/8a$	1
	Chipped glass	Chipped glass $Z \leq 1/2t$ $\therefore If there are 2 or model6.1.2 Corner crack:$ $$ $$ $$ $$ $$ $$	Chipped glass $Z \leq 1/2t$ Not over viewing area $1/2t < z \leq 2t$ Not exceed $1/3k$ \odot If there are 2 or more chips, x is total length $6.1.2$ Corner crack: \checkmark </td <td>Chipped glass$Z \leq 1/2t$Not over viewing area$x \leq 1/8a$$1/2t < z \leq 2t$Not exceed $1/3k$$x \leq 1/8a$$\odot$ If there are 2 or more chips, x is total length of each chip.$6.1.2$ Corner crack:\checkmark</td>	Chipped glass $Z \leq 1/2t$ Not over viewing area $x \leq 1/8a$ $1/2t < z \leq 2t$ Not exceed $1/3k$ $x \leq 1/8a$ \odot If there are 2 or more chips, x is total length of each chip. $6.1.2$ Corner crack: \checkmark



NO	Item	Criterion	AQL
07	Cracked glass	The LCD with extensive crack is not acceptable.	2.5
		8.1 Illumination source flickers when lit.	0.65
08	Backlight elements	8.2 Spots or scratched that appear when lit must be judged. Using LCD spot, lines and contamination standards.	2.5
		8.3 Backlight doesn't light or color wrong.	0.65
09	Bezel	9.1 Bezel may not have rust, be deformed or have fingerprints, stains or other contamination.	2.5
		9.2 Bezel must comply with job specifications.	0.65
		10.1 COB seal may not have pinholes larger than 0.2mm or contamination.	2.5
		10.2 COB seal surface may not have pinholes through to the IC.	2.5
		10.3 The height of the COB should not exceed the height indicated in the assembly diagram.	
		10.4 There may not be more than 2mm of sealant outside the seal area on the PCB. And there should be no more than three places.	
		10.5 No oxidation or contamination PCB terminals.	2.5
		10.6 Parts on PCB must be the same as on the production	
10	PCB \ COB	characteristic chart. There should be no wrong parts, missing parts or excess parts.	
		10.7 The jumper on the PCB should conform to the product characteristic chart.	0.65
		10.8 If solder gets on bezel tab pads, LED pad, zebra pad or screw hold pad, make sure it is smoothed down.	2.5
		10.9 The Scraping testing standard for Copper Coating of PCB	2.5
		$\mathbf{X} \mathbf{X} \mathbf{X} \mathbf{X} \mathbf{X} \mathbf{X} \mathbf{X} \mathbf{X} $	
_		11.1 No un-melted solder paste may be present on the PCB.	2.5
		11.2 No cold solder joints, missing solder connections,	2.5
11	Soldering	oxidation or icicle.	
		11.3 No residue or solder balls on PCB.	2.5
		11.4 No short circuits in components on PCB.	0.65

NO	Item	Criterion	AQL
		12.1 No oxidation, contamination, curves or, bends on interface	2.5
		Pin (OLB) of TCP.	
		12.2 No cracks on interface pin (OLB) of TCP.	0.65
		12.3 No contamination, solder residue or solder balls on product.	2.5
		12.4 The IC on the TCP may not be damaged, circuits.	2.5
		12.5 The uppermost edge of the protective strip on the interface	2.5
		pin must be present or look as if it cause the interface pin to sever.	
		12.6 The residual rosin or tin oil of soldering (component or chip	2.5
12	General	component) is not burned into brown or black color.	
	appearance	12.7 Sealant on top of the ITO circuit has not hardened.	2.5
		12.8 Pin type must match type in specification sheet.	0.65
		12.9 LCD pin loose or missing pins.	0.65
		12.10 Product packaging must the same as specified on packaging	0.65
		specification sheet.	
		12.11 Product dimension and structure must conform to product	0.65
		specification sheet.	
		12.12 Visual defect outside of VA is not considered to be rejection.	0.65

<u>13.Material List of Components for</u> <u>RoHs</u>

 WINSTAR Display Co., Ltd hereby declares that all of or part of products (with the mark "#"in code), including, but not limited to, the LCM, accessories or packages, manufactured and/or delivered to your company (including your subsidiaries and affiliated company) directly or indirectly by our company (including our subsidiaries or affiliated companies) do not intentionally contain any of the substances listed in all applicable EU directives and regulations, including the following substances.

Exhibit A: The Harmful Material List

Material	Cd	Pb	Hg	Cr6+	PBB	PBDE	DEHP	BBP	DBP	DIBP
Limited	100	1000	1000	1000	1000	1000	1000	1000	1000	1000
Value	ppm	ppm	ppm	ppm	ppm	ppm	ppm	ppm	ppm	ppm
Above limited value is set up according to RoHS.										

2.Process for RoHS requirement : (only for RoHS inspection)

- (1) Use the Sn/Ag/Cu soldering surface ; the surface of Pb-free solder is rougher than we used before.
- (2) Heat-resistance temp. :

Reflow : 250° C, 30 seconds Max. ;

Connector soldering wave or hand soldering $: 320^{\circ}$ C, 10 seconds max.

(3) Temp. curve of reflow, max. Temp. : $235\pm5^{\circ}C$;

Recommended customer's soldering temp. of connector : 280°C, 3 seconds.

14.Recommendable Storage

- 1. Place the panel or module in the temperature 25°C±5°C and the humidity below 65% RH
- 2. Do not place the module near organics solvents or corrosive gases.
- 3. Do not crush, shake, or jolt the module.

winstar <u>LCM Samp</u> odule Number:		<u>Feedback Sheet</u> Page: 1
1 <u> Panel Specification</u> :		
1. Panel Type :	Pass	🗌 NG ,
2. View Direction :	Pass	□ NG ,
3. Numbers of Dots :	Pass	□ NG ,
4. View Area :	Pass	□ NG ,
5. Active Area :	Pass	□ NG ,
6. Operating Temperature :	Pass	□ NG ,
7. Storage Temperature :	Pass	□ NG ,
8. Others :		
2 <u>Mechanical Specification</u> :		
1. PCB Size :	Pass	□ NG ,
2. Frame Size :	Pass	□ NG ,
3. Materal of Frame :	Pass	□ NG ,
4. Connector Position :	Pass	□ NG ,
5. Fix Hole Position :	Pass	□ NG ,
6. Backlight Position :	Pass	□ NG ,
7. Thickness of PCB :	Pass	□ NG ,
8. Height of Frame to PCB :	Pass	□ NG ,
9. Height of Module :	Pass	□ NG ,
10. Others :	Pass	□ NG ,
3 \ <u>Relative Hole Size</u> :		
1. Pitch of Connector :	Pass	□ NG ,
2. Hole size of Connector :	Pass	□ NG ,
3. Mounting Hole size :	Pass	□ NG ,
4. Mounting Hole Type :	Pass	□ NG ,
5. Others :	Pass	□ NG ,
4 <u>Backlight Specification</u> :		
1. B/L Type :	Pass	□ NG ,
2. B/L Color :	Pass	□ NG ,
3. B/L Driving Voltage (Refere	nce for LED T	$Fype): \square Pass \square NG, _$
4. B/L Driving Current :	Pass	□ NG ,
5. Brightness of B/L :	Pass	□ NG ,
6. B/L Solder Method :	Pass	□ NG ,
7. Others :	Pass	□ NG ,



winstar

Module Number : _____

- 1. Input Voltage :
 □ Pass

 2. Supply Current :
 □ Pass
- 3. Driving Voltage for LCD : Pass
- 4. Contrast for LCD : Pass

Pass

Pass

Pass

- 8. LCD Uniformity :
- 9. ESD test :
- 10. Others :

6 \ <u>Summary</u> :

Page: 2

Sales signature : _____

Customer Signature :

Date	:	1	/	